

LiveNoise Terminal with Low Cost Microphone



Features

- Monitors and Stores Sound Levels
- Network Connection (WiFi or Ethernet)
- Easily Wall Mounted
- Accurate Sound Level Indicator

Applications

- Office Noise
- High Noise Level Alarm
- Steam Leak Monitoring

Low Cost Noise Monitor

This LiveNoise monitor is fitted with a low cost microphone. While it gives an accurate measurement of the relative sound level, it is not intended for applications that need a monitor meeting standards such as IEC 61672 and ANSI S1.4. Please see our other noise monitors for these applications.


The LNT-M is ideal for monitoring long term relative noise levels and warning when levels go unexpectedly high. A typical application would be monitoring for high pressure steam leaks in an industrial environment.

It is also ideal for monitoring the noise levels in open plan offices. A mixed system including this low cost version along with the LNT-320 or LNT-EAR noise monitors can be used to monitor larger areas with additional accuracy at key locations.

The noise monitor can communicate continuously with the LiveNoise Supervisor software to provide real-time noise levels, long-term stored noise measurements and high-noise alarms. The LiveNoise Reporter software can generate long term reports.

Alternatively, you can use the Web Reporter for online noise reports.

An HDMI monitor can be connected to provide a large display of sound levels. The display can even be an old VGA monitor that you have hanging around, but you will need an HDMI to VGA adapter.



LiveNoise Terminal with Low Cost Microphone

Specifications

Technical Specifications

Measuring Range	50 to 120 dB
Frequency Weighting	"A"
Noise Measurements	Leq, Fast Sound Level
USB Port	For USB memory stick configuration and keyboard
Ethernet Port	RJ45 socket
Video Output	HDMI
Internal Memory	16 GB for up to 5 years storage
Dimensions	70 x 88 x 29 mm, 2.8" x 3.5" x 1.2"
Power	5 VDC, max 12W (power adapter included)

LiveNoise LNT-M Dimensions

Head Office

NoiseMeters Inc
3233 Coolidge Hwy
Berkley
MI 48072
USA

Telephone **888 206 4377**
Fax **888 584 2230**

Email: **info@noisemeters.ca**
Support: **support@noisemeters.ca**

Web Sites

Main site:
<https://noisemeters.ca>

Product shortcut:
<https://noisemeters.ca/product/livenoise1/lnt-m/>

Tech Support:
<https://support.noisemeters.com>