

## SoundEar 3 XL Extra Large Warning Sign



### Features

- Individual noise trigger levels for red, yellow and green
- Digital display of sound level in dB
- Data logging with download to USB stick
- Outputs also available via 4-20mA current loop or 0-10V DC

### Applications

- Factories
- Industrial sites
- Hearing protection - time to act
- Intermittent Noise - warn when it gets high

### Overview

The SoundEar 3 XL is an Extra Large version for the standard SoundEar 3 Industrial Noise Sign. It is about twice as tall and twice as wide as the standard unit.

This version of the SoundEar Industrial is ideal for larger areas where the standard industrial noise sign may not be visible enough.

### Instant Warning

The SoundEar 3 XL Industrial is usually set up to let people know that the sound levels are getting high, with the red light coming on when action needs to be taken - either reduce the levels or use hearing protection. There are many ways to configure this version of the noise sign. Please visit the Displays page for more information.

Each of the lights (green, yellow, red) can be configured to come on at different levels, and they can flash for better visibility. A common setting would be to have the green light on the time, to remind people that the sound levels are being monitored, the yellow light could be set to light up when the surrounding noise is 80dB(A) and the red light flashing when it exceeds 85dB(A).

### Data Logging and Software

The SoundEar 3 XL Industrial has a large internal memory that stores the sound level every second. When downloaded to a computer this gives a detailed graph of the noise throughout the day. A USB memory stick is the easiest way to transfer the noise measurements from the SoundEar XL to a computer. More information on the **Software** tab.

### Outputs and System Integration

The SoundEar 3 XL Industrial can output the sound level in two different forms, making it suitable for integration with other monitoring and control systems. Using the software supplied you can configure the outputs to be either DC 0 to 10V or current loop 4-20mA. Two outputs are available and can be set to different noise parameters.

### External Microphone

The SoundEar 3 XL Industrial has a plug-in microphone. It connects at the bottom of the sign and remains out of sight and out of harm's way. If you need to mount the microphone away from the sign then you can use a microphone extension cable, which should be ordered separately, order code SE3EXT.

## SoundEar 3 XL Extra Large Warning Sign

### Specifications

#### Technical Specifications

Frequency Range	20Hz to 20kHz
Measuring Range	30 to 120 dB
Deviation	± 0.5 dB
Frequency Weighting	"A" ("C" weighted Peak)
Time Weighting	Fast and Slow
Digital Display	LAeq,1s, Alarm Level, Clock
Outputs	"A" weighted, 0-10V or 4-20mA
USB Ports	1. Micro USB (power and PC connection) 2. USB Controller (for USB memory stick connection)
Internal Memory	16MB (128MBit) - 600 days
Dimensions	595 x 412 x 59 mm, 23.4" x 16.2" x 2.3"
Power	5 VDC (micro USB) or 24 VDC (screw terminal) Max 2.5W
Acoustic Standards	IEC61672-2-2002 Class 2, ANSI S1.4 Type 2

---

#### Head Office

NoiseMeters Inc  
3233 Coolidge Hwy  
Berkley  
MI 48072  
USA

Telephone **888 206 4377**  
Fax **888 584 2230**

Email: **info@noisemeters.ca**  
Support: **support@noisemeters.ca**

#### Web Sites

Main site:  
<https://noisemeters.ca>

Product shortcut:  
<https://noisemeters.ca/p/se3indx/>

Tech Support:  
<https://support.noisemeters.com>